

Cloud CX462 Jumper Settings



| Ref | Description | Default | Location | Notes |
|-----|---------------------------------------|---------|-------------------------|----------|
| J1 | Mic 1 access bypass | ON | Rear Right: Main PCB | CX462 |
| J2 | Mic 2 access bypass | ON | Rear Right: Main PCB | CX462 |
| J3 | Mic 3 access bypass | ON | Rear Right: Main PCB | CX462 |
| J4 | Mic 4 access bypass | ON | Rear Right: Main PCB | CX462 |
| J5 | Mic 3 Phantom Power | OFF | Rear Right: Main PCB | CX462 |
| J6 | Mic 4 Phantom Power | OFF | Rear Right: Main PCB | CX462 |
| J7 | Force Analogue Control of Source | SW | Rear Right: Main PCB | CX462 |
| J8 | Force analogue Control of Level | SW | Rear Right: Main PCB | CX462 |
| J9 | Force Front Panel Control of Source | SW | Rear Right: Main PCB | CX462 |
| J10 | Force Front Panel Control of Level | SW | Rear Right: Main PCB | CX462 |
| J11 | Line 6 Priority enable (dual jumpers) | OFF | Mid Left: Main PCB | CX462 |
| J12 | Line 6 Priority release | 3s | Mid Left: Main PCB | CX462 |
| J13 | Music Mute | NO | Rear Left: Main PCB | CX462 |
| J14 | Music Outputs Mono Stereo | Stereo | Rear Right: Main PCB | CX462 |
| J15 | Microphone over Music priority | POST | Front Right: Lower PCB | CX462 |
| J16 | Mic 1 over music priority trigger | AVO | Front Mid: Main PCB | CX462 |
| J17 | Mic 1 over mics priority trigger | AVO | Front Mid: Main PCB | CX462 |
| J18 | Mic 1 Phantom Power | OFF | Rear Right: Mic PCB | CX462 |
| J19 | Mic 2 Phantom Power. | OFF | Rear Right: Mic PCB | CX462 |
| | | | | |
| J1 | Baud Rate | 9600 | Rear Left: CDI-S100 PCB | CDI-S100 |
| J2 | Baud Rate | 9600 | Rear Left: CDI-S100 PCB | CDI-S100 |
| J3 | Baud Rate | 9600 | Rear Left: CDI-S100 PCB | CDI-S100 |
| J4 | Control (RTS/CTS, XON/XOFF/NONE) | NONE | Rear Left: CDI-S100 PCB | CDI-S100 |
| J5 | Control (RTS/CTS, XON/XOFF/NONE) | NONE | Rear Left: CDI-S100 PCB | CDI-S100 |

General Notes:

- All power to the unit must be removed before removing the top panel

Cloud Electronics Limited

140 Staniforth Road, Sheffield, S9 3HF. England
 Telephone: +44 (0)114 244 7051 Fax: +44 (0)114 242 5462
 Web: www.cloud.co.uk E-mail: info@cloud.co.uk

Cloud Electronics USA

2065 Sidewinder Drive, Suite 200, Park City,
 Utah 84060. United States of America.
 Toll Free: 0855 810 0161
 Web: www.cloudusa.pro E-mail: sales@cloudusa.pro